

Flex Max® RF Amplifiers

FM601e-LE

1 GHz Line Extender Amplifiers

FEATURES

- Simplify plant upgrades with modular RF design
- Maintain current amplifier spacing with high output GaAs technology
- Maintain installed base with RF module support for 9-NH15 and legacy 9-NH housings
- Expand return path bandwidth with plug-in diplex filter support to 85 MHz
- Minimize RF drift over temperature with standard analog or QAM ALC

For cable operators looking to ensure scalability, maximum backward compatibility, and protect network investments, CommScope offers solutions that deliver new services with minimal CAPEX, enhance network efficiency, and increase subscriber satisfaction.

CommScope Flex Max® FM601e-LE 1 GHz Line Extender Amplifiers are designed to easily and cost effectively increase bandwidth from 750/870 MHz to 1 GHz in legacy Philips networks. Featuring 1 GHz GaAs technology, the FM601e-LE is available as a complete unit for greenfield deployments or as a drop-in RF module for Philips 9-NH15 and 9-NH series housings. In addition, the FM601e-LE is compatible with 750/870 MHz EQs and Pads, allowing operators to extend or upgrade Philips amplifier networks quickly and easily using common plug-ins. The unit features return input pad location, and auxiliary forward interstage pad location, and customer accessible surge terminator for easy installation and maintenance.



CommScope also offers a QAM Channel Automatic Level Control (ALC) Pilot Frequency option, which is available with or without a gain hold feature, for Flex Max Amplifiers. An option with the gain hold feature enables an amplifier to adjust output levels to the mid-range automatically if its pilot level drops by 10 dB or more. The ALC Pilot Frequency option allows operators to choose between 609 MHz or 711 MHz pilot frequencies.

PLATFORM COMPATIBILITY

Platform	Philips Diamond Line III (G3A61X)	FM601-LE
Upgrade to FM601e-LE	Yes*	Yes

*Requires 15A Seizure Pin (PN 0512842-3)

HOUSING COMPATIBILITY

Housing	7-NH	9-NH	9-NH15
Upgrade to FM601e	Yes*	Yes*	Yes

*Requires 15A Seizure Pin (PN 0512842-3)

SPECIFICATIONS GaAs (ALC)

Specifications	Forward	Return
Frequency Split, MHz	54–1002 85–1002	5–42 5–65
Flatness, dB	± 0.8	± 0.8
Full Gain (without EQ and ALC), dB	37	19
Operation Gain (-0,+1.0 dB), dB ^{1,2}	33	18
ALC Control Range, dB	± 3.0	NA
Noise Figure (without EQ), dB ³	10/9.5/9/10	15.5
Standard Slope Reference Frequency, MHz	1002/870/550/54	F _{MAXRTN} /5
Reference Output Level, dBmV ^{5,6}	52/49.5/44/35	35/35
Operating Tilt, dB	17	NA
Carrier to Interference Ratio		
Channels, Number of NTSC ⁴	79	6
Composite Triple Beat (CTB), -dBc	72	80
Cross Modulation (XM), -dB	66	74
Composite Second Order (CSO), -dBc	69	82
Carrier to Intermodulation Noise (CIN), dB ⁷	71	—
Channels, Number of 256 QAM ⁸	154	—
Carrier to Intermodulation Noise (CIN), dB ⁹	63	—
Test Point Accuracy (-20 dB), dB		
Input Test Point	± 0.5 (54–550), ± 1.0 (551–1002)	± 0.75 (5 – F _{MAXRTN})
Output Test Point	± 0.5 (54–550), ± 1.0 (551–1002)	± 0.5 (5 – F _{MAXRTN})
Return Loss, dB	16	16
Hum Modulation @ 15A, -dBc		
5–10 MHz	—	55
11–F _{MAXRTN} MHz	—	65
54–1002 MHz	60	—
DC Voltage, VDC	24 ± 0.5	
Current DC Max/Typical, mA	965/890	
Power Consumption Max/Typical, W	29/24.5	
Input Voltage Range, VAC		
90 VAC HFC	45–90	
HFC AC Current Draw Max/Typical, A ¹⁰		
@ 90 VAC	0.405/.34	
@ 60 VAC	.655/.555	
AC Bypass Current (all ports), A	15	
Chrominance/Luminance Delay, ns/3.58 MHz		
Channel 2	28	—
Channel 3	12	—
Channel 4	7	—
Channel 5	4	—
Return Group Delay, ns		
5.5–7 MHz	—	55
10–11.5 MHz	—	10
35–36.5 MHz	—	10
38.5–40 MHz	—	30

SPECIFICATIONS MECHANICAL

Specifications	
Operating Temperature Range	-40° to +60°C -40° to +140°F
Housing Dimensions, L x W x D	15.5 L x 9.1 W x 5.3 D inches 394 L x 231 W x 135 D mm
Weight	15.9 lb 7.2 kg

NOTES:

1. Forward spacing at highest frequency with PEQ-1G-xx equalizer installed.
2. Return spacing is with a 0 dB attenuator installed in the return EQ location. Return EQ circuitry is built into main PCB. As the attenuator value increases, the return equalization insertion loss at F_{MAXRTN} MHz also increases.
3. The noise figure specification is "Typical" within specified passband.
4. Analog channels occupying the 54 to 550 MHz frequency range with 256-QAM channels to 1002 MHz at -6 dBc below equivalent video channels.
5. Recommended maximum return output level includes loss due to equalizer.
6. At specified operational tilt, maximum equivalent analog output level for 1 GHz loading is 56.5 dBmV @ HF for GaAs.
7. Systems operating with digitally compressed channels or equivalent broadband noise from 550 to 1002 MHz at levels 6 dB below equivalent video channels will experience a composite intermodulation distortion (CIN) appearing as noise in the 54 to 550 MHz frequency spectrum.
8. 256-QAM channels occupy 54 to 1002 MHz with 3 channels replaced by analog channels for CCNR measurement.
9. Systems operating with digitally compressed channels from 54 to 1002 MHz at levels 6 dB below equivalent video channels will experience a composite intermodulation distortion (CIN) appearing as noise relative to any remaining analog channels.
10. The power supply is internal to the RF module. Refer to drawing #333995-37.
For 60 VAC powering: AC power consumption in watts divided by a factor of 43 = Amps required.
For 90 VAC powering: 67 VAC, 1.03 x (AC power consumption in watts divided by voltage) = Amps required.
For 67 to 90 VAC, AC power consumption in watts divided by 65 = Amps required.

REQUIRED ACCESSORIES

Part Number	Description
PEQ-1G-00	One of the following per FM601e Forward 1002 MHz equalizer (0 dB) -or-
PEQ-1G-XX	Forward 1002 MHz equalizer (values 2 to 20 dB in 1 dB steps) -or-
PCS-1G-XX	Cable simulator (values 2 to 12 dB in 1 dB steps)
7-REFxx/x-WC	Plug-in Return Equalizer (values 1 to 9 dB in 1 dB steps)
10Axx.0-WC	Plug-in Attenuators (values 0 to 26 dB in 1 dB steps)

OPTIONAL ACCESSORIES

Part Number	Description
0512842-3	FM601/TNA/GNA/DL – 15 Amp Seizure Pin with spacer

RELATED PRODUCTS

FM321e-LE	FM601e-T/B
FM901e-T/B	STARLINE™ RF Amplifiers
FM331-LE	Installation Services

Contact Customer Care for product information and sales:

- United States: 866-36-ARRIS
- International: +1-678-473-5656



Note: Specifications are subject to change without notice.

Copyright Statement: © 2021 CommScope, Inc. All rights reserved. ARRIS, the ARRIS logo, Flex Max, and STARLINE are trademarks of CommScope, Inc. and/or its affiliates. All other trademarks are the property of their respective owners. No part of this content may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from CommScope, Inc and/or its affiliates ("CommScope"). CommScope reserves the right to revise or change this content from time to time without obligation on the part of CommScope to provide notification of such revision or change.

FM601eLE_DS_17SEP21