

FBR-COIL-S

HELIX® Discrete Fiber Storage Coiler - Small Patent Pending

Bulletin 7841813 Revision C Page 1 of 1

Hardware Included:




Qty: 2

Locking head



Qty: 2 x 2ft
Acetel Cable
banding



Qty: 4
Tie wraps
(stacking only)

Replacement Hardware:

Locking Head	CB-LH-25 (kit of 25)
Cable banding	CB-12-50 (50ft)
Tie wrap	CT-460-100 (kit of 100)

1 Discrete Fiber Storage Coiler can be mounted to a pipe or angle iron using the provided hardware. For flat surface mounting contractor needs to provide appropriate hardware.

2 Coiler may be installed vertically or horizontally. Select the correct mounting notches and install the banding.

3 Mount coiler to structure by sliding the ends of banding into locking head, pull uniformly to tighten. Installation tool CB-IT is recommended for tightening banding (sold separately).

4 Route cable to determine excess cable length. The coiler will hold a maximum of 16 feet (5 meters) of excess 7mm cable.

5 Coilers can be triple stacked when mounted to a pipe, angle iron or a flat surface. Slide coiler **2** over the alignment pins of coiler **1**. Secure coiler **2** to coiler **1** using provided tie wraps. Place the tie wraps on opposite ends of each other. Coil the excess cable to secure cable to the coiler. If 3rd coiler is required repeat steps.

3 stack maximum

CommScope

1100 CommScope Place SE P.O. Box 339, Hickory, NC 28603-0339
(828) 324-2200 (800) 982-1708
www.commscope.com

Notice: CommScope disclaims any liability or responsibility for the results of improper or unsafe installation, inspection, maintenance, or removal practices.

Aviso: CommScope no acepta ninguna obligación ni responsabilidad como resultado de prácticas incorrectas o peligrosas de instalación, inspección, mantenimiento o retiro.

Avis : CommScope décline toute responsabilité pour les conséquences de procédures d'installation, d'inspection, d'entretien ou de retrait incorrectes ou dangereuses.

Hinweis: CommScope lehnt jede Haftung oder Verantwortung für Schäden ab, die aufgrund unsachgemäßer Installation, Überprüfung, Wartung oder Demontage auftreten.

Atenção: A CommScope abdica do direito de toda responsabilidade pelos resultados de práticas inadequadas e sem segurança de instalação, inspeção, manutenção ou remoção.

Avvertenza: CommScope declina eventuali responsabilità derivanti dall'esecuzione di procedure di installazione, ispezione, manutenzione e smontaggio improprie o poco sicure.

注意: CommScope 公司申明對於不恰當或不安全的安裝、檢驗、維修或拆卸操作所導致的後果不負責任 何義務和責任

© 2021 CommScope

Technical Support

+1 888 297 6433, Option 3 (Toll Free US and Canada)
+49-9099-69-333

<https://www.commscope.com/wisupport> (open a ticket)