## FFV4-65C-R6-V2



# 12-port sector antenna, 4x 617-894 and 8x 1695–2690 MHz, 65° HPBW, 6x RET

• Antenna includes 2x Single Column X-Pol Arrays for 617-894MHz and 4x Single Column X-Pol Arrays for 1695-2690MHz, suitable for 4x MIMO applications

### General Specifications

Antenna Type	Sector
Band	Multiband
Color	Light Gray (RAL 7035)
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage
Radome Material	Fiberglass, UV resistant
Radiator Material	Low loss circuit board
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, high band	8
RF Connector Quantity, mid band	0
RF Connector Quantity, low band	4
RF Connector Quantity, total	12

#### Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	8-pin DIN Female   8-pin DIN Male
RET Interface, quantity	1 female   1 male
Input Voltage	10-30 Vdc
Internal RET	High band (4)   Low band (2)
Power Consumption, active state, maximum	8 W
Power Consumption, idle state, maximum	1 W
Protocol	3GPP/AISG 2.0 (Single RET)

Page 1 of 8



#### Dimensions

Width	498 mm   19.606 in
Depth	197 mm   7.756 in
Length	2438 mm   95.984 in
Net Weight, antenna only	40.5 kg   89.287 lb

### Array Layout

				_					
					Array	Freq (MHz)	Conns	RET (SRET)	AISG RET UID
					R1	617-894	1-2	1	CPxxxxxxxxxxxR1
					R2	617-894	3-4	2	CPxxxxxxxxxxxxR2
					Y1	1695-2690	5-6	3	CPxxxxxxxxxxxxxXXXXXXXXY1
					Y2	1695-2690	7-8	4	CPxxxxxxxxxxxxXXXXXXXXXXY2
Y1	¥2	Y3	¥4		Y3	1695-2690	9-10	5	CPxxxxxxxxxxxxXXXXXXXXXXXXXXXXXXXXXXXXX
	R1	R			¥4	1695-2690	11-12	6	CPxxxxxxxxxxxxxXXXXXY4
		_							

Left Right Bottom

(Sizes of colored boxes are not true depictions of array sizes)

### Port Configuration

Page 2 of 8





#### Electrical Specifications

Impedance	50 ohm
Operating Frequency Band	1695 – 2690 MHz   617 – 894 MHz
Polarization	±45°
Total Input Power, maximum	1,400 W @ 50 °C

### **Electrical Specifications**

Frequency Band, MHz	617-698	698-894	1695-1880	1850-1990	1920-2200	2300-2500	2500-2690
RF Port	1-4	1-4	5-12	5-12	5-12	5-12	5-12
Gain, dBi	14.8	15.5	16.6	17	17.3	17.6	18
Beamwidth, Horizontal, degrees	65	57	64	65	63	58	57
Beamwidth, Vertical, degrees	10.2	8.7	6.6	6.3	6	5.3	5.1
Beam Tilt, degrees	2-13	2-13	2-12	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	19	18	18	18	19	20	19
Front-to-Back Ratio at 180°, dB	30	31	35	35	33	31	28
Isolation, Cross Polarization, dB	25	25	25	25	25	25	25





# FFV4-65C-R6-V2

Isolation, Inter-band, dB	25	25	25	25	25	25	25
VSWR   Return loss, dB	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0
PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150	-150
Input Power per Port at 50°C, maximum, watts	250	250	200	200	200	200	200

#### Mechanical Specifications

Wind Loading @ Velocity, frontal	829.0 N @ 150 km/h (186.4 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	217.0 N @ 150 km/h (48.8 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	1,102.0 N @ 150 km/h (247.7 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	570.0 N @ 150 km/h (128.1 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

#### Packaging and Weights

Width, packed	565 mm   22.244 in
Depth, packed	309 mm   12.165 in
Length, packed	2685 mm   105.709 in
Weight, gross	61.4 kg   135.364 lb

#### Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.andrew.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant



#### Included Products

BSAMNT-3	-	Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.
BSAMNT-M	-	Middle Downtilt Mounting Kit for Long Antennas for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor bracket set.

#### \* Footnotes

Page 4 of 8



FFV4-65C-R6-V2

Performance Note

Severe environmental conditions may degrade optimum performance

Page 5 of 8



# BSAMNT-3



Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

Product Classification	
Product Type	Downtilt mounting kit
General Specifications	
Application	Outdoor
Color	Silver
Dimensions	
Compatible Diameter, maximum	115 mm   4.528 in
Compatible Diameter, minimum	60 mm   2.362 in
Weight, net	6.2 kg   13.669 lb
Material Specifications	
Material Type	Galvanized steel
Packaging and Weights	
Included	Brackets   Hardware
Packaging quantity	1
Weight, gross	6.4 kg   14.11 lb
morgin, gross	

#### Regulatory Compliance/Certifications

Agency	Classification
CE	Compliant with the relevant CE product directives
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.andrew.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant

ANDREW an Amphenol company

Page 6 of 8





Page 7 of 8



# BSAMNT-M



Middle Downtilt Mounting Kit for Long Antennas for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor bracket set.

Product Classification	
Product Type	Downtilt mounting kit
General Specifications	
Application	Outdoor
Color	Silver
Dimensions	
Compatible Diameter, maximum	115 mm   4.528 in
Compatible Diameter, minimum	60 mm   2.362 in
Weight, net	4.5 kg   9.921 lb
Material Specifications	
Material Type	Galvanized steel
Packaging and Weights	
Included	Brackets   Hardware
Packaging quantity	1

#### Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.andrew.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant



Page 8 of 8

